

PARTS LIST AND DESCRIPTIONS (Continued)

RESISTORS

All wattages 1/2 watt, or less, unless otherwise listed.

ITEM No.	RATING		REPLACEMENT DATA		NOTES
	OHMS	WATT	KNIGHT PART No.	IRC PART No.	
R5	10Meg			BTS-10Meg	
R6	220K			BTS-220K	
R7	10Meg			BTS-10Meg	
R8	100K			BTS-100K	
R9	220K			BTS-220K	
R10	47K			BTS-47K	
R11	100K			BTS-100K	
R12	22K			BTS-22K	
R13	180K			BTS-180K	
R14	1800Ω			BTS-1800	
R15	1.5Meg			BTS-1.5Meg	
R16				BTS-10K	
R17				BTS-10K	
R18				BTS-10K	
R19				BTS-470K	
R20				BTS-470K	
R21				BTS-470K	
R22				BTS-470K	
R23				BTS-10K	
R24				BTS-470K	
R25				PW10-200	
				PW10-7500	

TRANSFORMER (POWER)

ITEM No.	RATING			REPLACEMENT DATA		
	PRI.	SEC. 1	SEC. 2	KNIGHT PART No.	Meritt PART No.	Stancor PART No.
T1	130V AC Tap @ 117V AC @ 1.18A	725VCT @ .135A	5VAC @ 3A	LP-0108-B		24R05 ①

① This Transformer Does Not Provide A Tap On Primary Winding For 130VAC Input.

TRANSFORMER (AUDIO OUTPUT)

ITEM No.	IMPEDANCE		REPLACEMENT DATA			NOTES
	PRI.	SEC.	KNIGHT PART No.	Meritt PART No.	Stancor PART No.	
T2	8000Ω	500Ω	LO-0083-D			
	Taps @ 250Ω, 181Ω, (70V), 161Ω, 81Ω, 4Ω					

MISCELLANEOUS

ITEM No.	PART NAME	KNIGHT PART No.	NOTES
M1	Pilot Light		#44
M2	Switch		Mag. - MIC 2, Slide Type (D. P. D. T.)

CHASSIS—BOTTOM VIEW

