

Part CHECK FOR ERRORS & compare with schematic !!	quantity = 1 unless listed otherwise	Source H= Hoffman O= other	Estimated Cost per unit @
PT Super Reverb 022798		H	
OT Super Reverb 018343 * has 2, 4, & 8 ohm taps make sure this matches your speaker set up		H	
Blank chassis	20" x 8" x 2.5"	turretboards.com	
Choke 3H 125C1		H	
Hoffman Tweed Overdrive turret board		H	
66 turrets (lugs)	* order 75 for xtra	H	
Shorting jacks switchcraft 12A	3	H	
speaker jack #11 switchcraft		H	
Pot 100kl Alpha	3	H	
Pot 1M Alpha	3	H	
Pots 250k Alpha	1	H	
Pot 500ka Alpha	1	H	
Pot 25 kl Alpha	2	H	
Filter cap 47uf/500v Illinois	1	H	
Filter cap 22uf/500v Illinois	3	H	
Filter cap 10uf/500 Sprague	2	H	
Filter cap 10uf/100v	1	H	
solid state rectifier plug		H	
9 pin ceramic sockets	3	H	
8 pin ceramic sockets	3	H	
250p Silver mica	1	H	
390p Silver mica	3	H	

.001	Orange Drop	2	H	
.002	Orange Drop		H	
.0047	Orange Drop	3	H	
.01	Orange Drop	1	H	
.02	Orange Drop	7	H	
.1	Xicon	1	H	
.68uf			H	
4.7uf		4	H	
1ohm 2w		2	H	
470 ohm 3w		2	H	
1k/3w			H	
2.2k/3w		2	H	
4.7k/3w			H	
10k/3w		2	H	
220k/3w			H	
250ohm/10w			H	
47 ohm			H	
100 ohm artificial htr grnd		2	H	
180 ohm used with LED light			H	
820R			H	
1.8k		2	H	
2.2k		2	H	
3.3k		2	H	
4.7k		2	H	
5.6k		2	H	
10k		3	H	
33k			H	
68k		2	H	

82k	2	H	
100k	2	H	
120k		H	
150k	2	H	
180k	2	H	
220k	3	H	
1M	3	H	
2.2M (for 4.4M)	2	H	
Or use 4.7M	1	O	
DPDT mini-toggle	2	H	
SPDT mini-toggle	2	O	
Wire red,white, green,black 20 gauge 8 ft of each		H	
Wire green, white (heaters) 6 ft 18 gauge		H	
Wire braided shielded 8ft		H	
AC receptacle and fuse holder		H	
Stand offs turret board 1/2" or your choice of height	6	H	
Knobs chicken head	10	H	
terminal strips (4open1gnd) 5 tag	2	H	
Carling on/off toggle switch	2	H	
LED on/off light		H	