

## Guild Thunderstar Bass

<u>Tube</u>	<u>Pin 1</u>	<u>Pin 2</u>	<u>Pin 3</u>	<u>Pin 4</u>	<u>Pin 5</u>	<u>Pin 6</u>	<u>Pin 7</u>	<u>Pin 8</u>	<u>Pin 9</u>
V1 - 12AX7	152	-4.0	1.0	--	--	150	-0.7	1.2	--
V2 - 7247	257	70	86	--	--	210	0	1.3	--
V3 - 6L6GC / 6P3S-E	NC	--	486	416	-48	NC	--	32mV	--
V4 - 6L6GC / 6P3S-E	NC	--	486	416	-49	NC	--	32mV	--

<u>Line in:</u>	123.4vAC
<u>After Thermistor:</u>	123.0vAC
<u>PT Secondary:</u>	190vAC
<u>Filament:</u>	6.9vAC
<u>B+1:</u>	490vDC
<u>B+2:</u>	416vDC
<u>B+3:</u>	346vDC
<u>B+4:</u>	300vDC
<u>Bias Supply Source:</u>	56vAC
<u>Bias Supply Rectified:</u>	-54vDC