

Luckey Deluxe Reverb
Single Channel AB763

Voltage Chart
4.11.18

TON Mod
450 V 430 V Plate

| | | | 3.25.18 | 4.11.18 | 3.21.20 | 3.24.20 | | | | 3.25.18 | 4.11.18 | 3.24.20 | |
|------|-------|-----|---------|---------|---------|---------|-----|------|------|---------|---------|---------|-----|
| V1-1 | 273.3 | V | 275.6 | 210 | 279 | 271 | V | V5-1 | 245 | 291 | 248 | 182 | V |
| V1-2 | 0 | V | 5.5 | 0 | 0 | | mV | V5-2 | 55 | 41 | 61.4 | 34.4 | V |
| V1-3 | 2.035 | V | 1.98 | 3.38 | 2.25 | 2.2 | V | V5-3 | 92 | 72 | 102 | 69 | V |
| V1-4 | 6.02 | VAC | 6.02 | 6.45 | 6.08 | 6.08 | | V5-4 | 6.04 | 6.47 | 6.08 | 6.08 | VAC |
| V1-5 | 6.02 | VAC | 6.02 | 6.45 | 6.08 | 6.08 | | V5-5 | 6.04 | 6.47 | 6.08 | 6.08 | VAC |
| V1-6 | 274.5 | V | 278.7 | 208 | 286.5 | 279 | V | V5-6 | 233 | 292 | 227 | 427 | V |
| V1-7 | 0 | | 0 | 0 | 0 | 0 | | V5-7 | 59 | 45 | 66.9 | 70 mV | V |
| V1-8 | 2.01 | V | 1.9 | 3.4 | 2.186 | 2.12 | V | V5-8 | 92 | 72 | 102 | 69 | V |
| V2-9 | 6.02 | VAC | 6.02 | 6.45 | 6.08 | 6.08 | | V5-9 | 6.04 | 6.47 | 6.08 | 6.08 | V |
| V2-1 | 392.6 | V | 428 | 447 | 447 | 435 | V | V6-1 | 24.6 | 24 | 33 | 51 | mV |
| V2-2 | 8.8 | mV | 9 | 8.5 | 10.5 | 9.3 | mV | V6-2 | 6.04 | 6.48 | 6.14 | 6.14 | VAC |
| V2-3 | 8.6 | V | 3.9 | 4.17 | 8.97 | 8.69 | V | V6-3 | 429 | 451 | 450 | 435 | V |
| V2-4 | 6.02 | VAC | 6.01 | 6.45 | 6.08 | 6.08 | | V6-4 | 429 | 451 | 450 | 435 | V |
| V2-5 | 6.02 | VAC | 6.01 | 6.45 | 6.08 | 6.08 | | V6-5 | 39 | 43 | 46 | 40 | V |
| V2-6 | 392.6 | V | 428 | 446 | 447 | 435 | V | V6-6 | 39 | 43 | 46 | 39 | V |
| V2-7 | 8.8 | mV | 8 | 9 | 8.3 | 8.8 | mV | V6-7 | 6.04 | 6.48 | 6.14 | 6.14 | VAC |
| V2-8 | 8.6 | V | 3.9 | 4.1 | 8.97 | 8.7 | V | V6-8 | 24.6 | 24 | 17 | 51 | mV |
| V2-9 | 6.02 | VAC | 6.01 | 6.45 | 6.08 | 6.08 | V | | | | | | |
| V3-1 | 278 | V | 202 | 212 | 278 | 271 | V | V7-1 | 25.7 | 24 | 33 | 50 | mV |
| V3-2 | 0 | mV | 0 | 0 | 0 | 0 | V | V7-2 | 6.06 | 6.48 | 6.14 | 6.14 | VAC |
| V3-3 | 1.95 | V | 3.1 | 3.39 | 2.25 | 2.2 | V | V7-3 | 428 | 450 | 450 | 436 | V |
| V3-4 | 6.01 | VAC | 6.01 | 6.46 | 6.08 | 6.08 | VAC | V7-4 | 430 | 451 | 450 | 436 | V |
| V3-5 | 6.01 | VAC | 6.01 | 6.46 | 6.08 | 6.08 | VAC | V7-5 | 39.2 | 43 | 46 | 40 | V |
| V3-6 | 0 | V | 199 | 210 | 0 | 277 | V | V7-6 | 39.2 | 43 | 46 | 39 | V |
| V3-7 | 0.5 | V | 0 | 20 | 0 | 0 | MV | V7-7 | 6.06 | 6.48 | 6.14 | 6.14 | VAC |
| V3-8 | 3.1 | V | 3.1 | 3.4 | 2.14 | 2.01 | V | V7-8 | 25.7 | 25 | 17 | 50 | mV |
| V3-9 | 6.01 | VAC | 6.01 | 6.46 | 6.08 | 6.08 | V | | | | | | |
| V4-1 | 236 | V | 238 | 235 | 236 | 370 | V | | | | | | |
| V4-2 | 1.5 | V | 1.5 | 1.6 | 0 | 0 | V | | | | | | |
| V4-3 | 1.8 | V | 1.9 | 3.4 | 1.47 | 4.6 | V | | | | | | |
| V4-4 | 6.03 | VAC | 6.03 | 6.47 | 6.08 | 6.08 | V | | | | | | |
| V4-5 | 6.03 | VAC | 6.03 | 6.47 | 6.08 | 6.08 | V | | | | | | |
| V4-6 | 424 | V | 430 | 452 | 0 | 437 | V | | | | | | |
| V4-7 | 236 | V | 239 | 249 | 0 | 369 | V | | | | | | |
| V4-8 | 240 | V | 244 | 248 | 0 | 380 | V | | | | | | |
| V4-9 | 6.03 | VAC | 6.03 | 6.47 | 6.08 | 6.08 | VAC | | | | | | |