

JCM25 PCB BOM

Ver C, 2020-07-13

Parts	Item	Position	Value	Power	amount
PCB	Resistor	R43,R44	100R	1/2W	2
PCB	Resistor	R42	1K	1/2W	1
PCB	Resistor	R28,R29	100R	1W	2
PCB	Resistor	R11	470R	1W	1
PCB	Resistor	R7	820R	1W	1
PCB	Resistor	R27	1K5	1W	1
PCB	Resistor	R2	2K7	1W	1
PCB	Resistor	R39	4K7	1W	1
PCB	Resistor	R13,R16	5K6	1W	2
PCB	Resistor	R1,R21	10K	1W	2
PCB	Resistor	R51	15K	1W	1
PCB	Resistor	R55	27K	1W	1
PCB	Resistor	R32	33K	1W	1
PCB	Resistor	R36	68K	1W	1
PCB	Resistor	R14	82K	1W	1
PCB	Resistor	R3,R4,R15,R53,R59 R35	100K	1W	6
PCB	Resistor	R22,R23	220K	1W	2
PCB	Resistor	R5,R6 R37	470K	1W	3
PCB	Resistor	R10,R12 R38	1M	1W	3
PCB	Resistor	R24C,R24D	1R	2W	2
PCB	Resistor	R25,R26	1K	2W	2
PCB	Resistor	R19,R20,R30	10K	2W	3
PCB	Resistor	R31	2K2	5W	1

Parts	Item	Position	Value	Power	amount
PCB	capacitance	C21	104	50V	1
PCB	capacitance	C2	684	50V	1
PCB	capacitance	C6,C53,C54	22U	50V	3
PCB	capacitance	C10	47P	400V	1
PCB	capacitance	C1	100P	400V	1
PCB	capacitance	C5 C20,C22	470P	400V	3
PCB	capacitance	C3,C4,C7,C9,C11 C18,C19	223	400V	7
PCB	capacitance	C8	104	400V	1
PCB	capacitance	C12,C13,C14	22U	450V	3
PCB	capacitance	C16,C17	47U	450V	2
PCB	Diode	D1,D2,D3,D4 D5,D6	1N4007		6
PCB	Micro VR	BIAS	B20K		1
PCB	Sockets	Guitar input	4 pins		2
PCB	VR	GAIN,LOW,MASTER	A1M		3
PCB	VR	MID,PRESENCE	B20K		2
PCB	VR	HIG	B250K		1
PCB	socket	V1,V2,V3	9 pins	Tube sockets	3
PCB	socket	V4,V5	8 pins	Tube sockets	2
assembly	socket	speaker out	5pins		3
assembly	socket	DI OUT	3pins	XRL	1
assembly	IEC plug	Power input			1
assembly	Fuse(IEC Plug)		3A/2A	120V/230V	1
assembly	Switch	Power			1
assembly	Switch	STANDBY	6pins	On-Off	1
assembly	Switch	P/T	6pins		1
assembly	LED	light	3脚	red-green	1
assembly	Power tranform	Power	GT30		1
assembly	output transfo	Output	6L6	3.5 Kohm	1
assembly	standoff	standoff PCB			9
assembly	Knobs				6