


RoadShow AB763 Voltage Chart

2025-06-19

122.3VAC

Bus Voltages => A = 445v dc B = 443v dc C = 432v dc D = 406v dc

V1 – 12AX7



Pre-amp

1	2	3	4	5	6	7	8	9
266	-	2.1	h	h	271	-	2.0	h

V2 – 12AT7

Reverb Driver

1	2	3	4	5	6	7	8	9
437	-	10.0	h	h	437	-	10.0	h

V3 – 12AX7

Reverb Recovery

1	2	3	4	5	6	7	8	9
273	-	2.0	h	h	269	-	2.03	h

V4 – 12AX7

Tremolo


1	2	3	4	5	6	7	8	9
181	-	1.66	h	h	442	181	185	h

V5 – 12AT7

Phase Inverter

1	2	3	4	5	6	7	8	9
240	-	93.0	h	h	250	61	93.0	h

V6 – 6L6GC



Output 1

1	2	3	4	5	6	7	8	Bias
-	h	441	441	-42	-42	h	40.8	60%


V7 – 6L6GC

Output 2

1	2	3	4	5	6	7	8	Bias
-	h	441	441	-46	-46	h	40.9	60%

V8 – 5AR4

Rectifier



1	2	3	4	5	6	7	8	
-	5.16 ac 445 dc		Diode	356 AC	Diode	356 AC	5.16ac 445 dc	