Fender AB763 Super Reverb Voltage Chart

All voltages are taken from the official Schematic	Normal Channel Stages 1&2	Tremolo Channel Stages 1&2	Reverb Driver	Reverb Recovery & stage 3	Tremolo Oscillator	Phase Inverter	Beam Power Tube	Beam Power Tube
Tube Position	**V1**	**V2**	**V3**	**V4**	**V5**	**V6**	**V7**	**V8**
	12AX7	12AX7	12AX7	12AX7	12AX7	12AX7	6L6GC	6L6GC
Pin 1	**270 VDC**	**270 VDC**	**450 VDC**	**270 VDC**	**230 VDC**	**230 VDC**		
Actual	**273**	**262**	**451**	**265**	**231**	**260**		
Pin 2	VDC	VDC	VDC	VDC	VDC	VDC	**3.1 VAC**	**3.1 VAC**
Actual						**60**		
Pin 3	**2.1 VDC**	**2.1 VDC**	**8.4 VDC**	**2.0 VDC**	**2.0 VDC**	**106 VDC**	**460 VDC**	**460 VDC**
Actual	**1.9**	**2.1**	**8.1**	**2.0**	**2.2**	**99**	**458**	**458**
Pin 4	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**458 VDC**	**458 VDC**
Actual							**458**	**458**
Pin 5	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**--52 VDC**	**--52 VDC**
Actual							**-51.5**	**-51.5**
Pin 6	**270 VDC**	**270 VDC**	**450 VDC**	**270 VDC**	**440 VDC**	**440 VDC**	**--52 VDC**	**--52 VDC**
Actual	**276**	**269**	**451**	**258**	**454**	**222**	**-51.5**	**-51.5**
Pin 7	VDC	VDC	**39 VDC**	VDC	**230 VDC**	VDC	**3.1 VAC**	**3.1 VAC**
Actual					**231**	**64**		
Pin 8	**2.1 VDC**	**2.1VDC**	**8.4 VDC**	**2.0 VDC**	VDC	**106 VDC**		
Actual	**1.8**	**1.95**	**8.1**	**2**	**239**	**99**		
Pin 9	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**	**3.1 VAC**		
Actual								