

Luckey Deluxe Reverb
Single Channel AB763

Voltage Chart 4.11.18			TON Mod				3.25.18						
			450 V	430 V	Plate								
			3.25.18	4.11.18	3.21.20	3.24.20				3.25.18	4.11.18		3.24.20
V1-1	273.3	V	275.6	210	279	271	V	V5-1	245	291	248	236	V
V1-2	0	V	5.5	0	0		mV	V5-2	55	41	61.4	60.4	V
V1-3	2.035	V	1.98	3.38	2.25	2.2	V	V5-3	92	72	102	101	V
V1-4	6.02	VAC	6.02	6.45	6.08	6.08		V5-4	6.04	6.47	6.08	6.08	VAC
V1-5	6.02	VAC	6.02	6.45	6.08	6.08		V5-5	6.04	6.47	6.08	6.08	VAC
V1-6	274.5	V	278.7	208	286.5	279	V	V5-6	233	292	227	219	V
V1-7	0		0	0	0	0		V5-7	59	45	66.9	66	V
V1-8	2.01	V	1.9	3.4	2.186	2.12	V	V5-8	92	72	102	101	V
V2-9	6.02	VAC	6.02	6.45	6.08	6.08		V5-9	6.04	6.47	6.08	6.08	V
V2-1	392.6	V	428	447	447	435	V	V6-1	24.6	24	33	51	mV
V2-2	8.8	mV	9	8.5	10.5	9.3	mV	V6-2	6.04	6.48	6.14	6.14	VAC
V2-3	8.6	V	3.9	4.17	8.97	8.69	V	V6-3	429	451	450	435	V
V2-4	6.02	VAC	6.01	6.45	6.08	6.08		V6-4	429	451	450	435	V
V2-5	6.02	VAC	6.01	6.45	6.08	6.08		V6-5	39	43	46	40	V
V2-6	392.6	V	428	446	447	435	V	V6-6	39	43	46	39	V
V2-7	8.8	mV	8	9	8.3	8.8	mV	V6-7	6.04	6.48	6.14	6.14	VAC
V2-8	8.6	V	3.9	4.1	8.97	8.7	V	V6-8	24.6	24	17	51	mV
V2-9	6.02	VAC	6.01	6.45	6.08	6.08	V						
V3-1	278	V	202	212	278	271	V	V7-1	25.7	24	33	50	mV
V3-2	0	mV	0	0	0	0	V	V7-2	6.06	6.48	6.14	6.14	VAC
V3-3	1.95	V	3.1	3.39	2.25	2.2	V	V7-3	428	450	450	436	V
V3-4	6.01	VAC	6.01	6.46	6.08	6.08	VAC	V7-4	430	451	450	436	V
V3-5	6.01	VAC	6.01	6.46	6.08	6.08	VAC	V7-5	39.2	43	46	40	V
V3-6	0	V	199	210	0	277	V	V7-6	39.2	43	46	39	V
V3-7	0.5	V	0	20	0	0	MV	V7-7	6.06	6.48	6.14	6.14	VAC
V3-8	3.1	V	3.1	3.4	2.14	2.01	V	V7-8	25.7	25	17	50	mV
V3-9	6.01	VAC	6.01	6.46	6.08	6.08	V						
V4-1	236	V	238	235	236	370	V						
V4-2	1.5	V	1.5	1.6	0	0	V						
V4-3	1.8	V	1.9	3.4	1.47	4.6	V						
V4-4	6.03	VAC	6.03	6.47	6.08	6.08	V						
V4-5	6.03	VAC	6.03	6.47	6.08	6.08	V						
V4-6	424	V	430	452	0	437	V						
V4-7	236	V	239	249	0	369	V						
V4-8	240	V	244	248	0	380	V						
V4-9	6.03	VAC	6.03	6.47	6.08	6.08	VAC						