



Tube Volt Chart

Pin	V1	V2	V3
1	242	217	n/c
2	g1	g1	fil
3	2.22	1.86	370
4	fil	fil	362
5	fil	fil	g1
6	n/c	216	n/c
7	n/c	g1	fil
8	n/c	1.50	27.9
9	fil	fil	n/a

Legend:
n/a = not applicable.
n/c = no connection.

Notes:
Approx 11W output depending on T2 Z, bias, etc..
T2 is 5K reflected; >= 75mA DC bias.
L1 is Hammond 3H, 100mA, model 156M choke.
All coupling caps are 400WVDC.
All bypass caps are 16VWDC, UON.
All resistors 1 watt metal film/foil, UON.

- Earth ground.
- Preamp ground - Input jack isolated.
- Power amp ground.
- Output ground - Jack grounded to chassis.

